

LUXA 103 S360-100-12 AP WH



?? ???? : 1030062 ????? ???? ???? ???? ? ???? ???? ???? : ????; 360 ???/????; 120???? ???? ???? : 230 VAC ????? ???? : 2 ?? 3 ???
???? ????? ? ???? ???? : 10 ????? - 20 ????? ???? ???? : IP 54

???? ???? : ???? ???? ???? ????
????

[?? ???? ?????? ??? ????? ??????](#)

???

Function description

- Passive infrared presence detector, surface-mounting
 - 1 channel light (relay 230 V)
 - Circular detection area 360°, Ø 12 m (113 m²)
- at 3 m mounting height
- Extension of the detection area by parallel switching, a maximum of 8 detectors can be connected in parallel
 - Networking with wall detector theMura Slave possible

- Connection option for push-button for manual switching
- Operation as fully or semi-automatic possible
- One directional brightness measurement (mixed light measurement)
- Teach-in function, pulse function, test function, staircase lighting function
- Ready for operation immediately due to factory presetting

???????? ??

???? ???? ???? ??? ?????? ????? ??????.

// //