


TR 612 top3



?? ?????:6120130 ????? ??????? ?????? ?? ?????? ??? ??? : ????? ????? ?????? : 230 VAC COS?=1 ? 16A COS?=0.6 ? 10A ????? ?????? : ?????  
56?????? ????? ?????? ????? ??1 ?????? ????? ?????? : IP 20

???? ?????: ????? ????? ????? ?????  
?????

[?? ????? ??????? ??? ????? ???????](#)

???

Function description

- Digital time switch with weekly program
- 2 channels
- Programming by app possible
- Safe transfer via optional Bluetooth Low Energy OBELISK top3
- Maximum manipulation security, time switch programs can only be transferred from the app to the time switch when the Bluetooth OBELISK top3 is plugged into the time switch
- 100 % compatible with top2
- DuoFix spring terminals
- For 2 conductors each

- Wire or strand (with or without wire end sleeve) •
  - Wire diameter: 0.5 - 2.5 mm<sup>2</sup> •
- Button for releasing plug-in connection •
- Text-oriented user guidance in display •
- Preset date and time •
- fully operable without mains connection •
- 56 memory locations •
- Interface for OBELISK top2 memory card (PC programming) •
- 2. insertable switching program •
- Copying programs •
- Storing programs •
- 10 year power reserve (lithium battery) •
- Zero-cross switching for relay-saving switching and high lamp loads (not with 24 V devices) •
- ON-OFF switching times •
- Switching preselection •
- Permanent switching ON/OFF •
- Integrated operating hour counter •
- Reset option •
- Service function for monitoring maintenance intervals •
- Holiday program •
- Display back light (can be turned off) •
- Permanent switching ON/OFF •
- PIN coding •
- Automatic summer/winter time changeover •
- can be deactivated •
- Date rule options are already stored for Europe, the USA and other countries •
- own date rule options or changeover around set dates are available •

???????? ??

???? ???? ???? ??? ????? ???? ?????.

// //